

Application of MgB₂ Wire to Liquid Hydrogen Level Sensor

–External-Heating-Type MgB₂ Level Sensor–*

M. Takeda¹, Y. Matsuno², I. Kodama², H. Kumakura³,
and C. Kazama¹

¹Graduate School of Maritime Sciences, Kobe University, JAPAN

²Iwatani Industrial Gases Corporation, JAPAN

³National Institute for Materials Science, JAPAN

* *IEEE Trans. Appl. Super.* Vol. 19 (2009) pp. 764-767.




Abstract

A superconducting magnesium diboride (MgB_2) level sensor for liquid hydrogen has been timely noted as a new sensor from a viewpoint of the worldwide storage and transport of large quantities of hydrogen. The external-heating-type level sensors (200 and 800 mm long) based on MgB_2 wires are fabricated by an in situ method, and their level-detecting characteristics are studied in comparison with the actual liquid level using the liquid hydrogen experiment facility (LHEF). It becomes evident that an external-heating-type MgB_2 level sensor has a high linearity, a small measurement error, and a good reproducibility even in the pressure range of up to 200 kPaG despite the evaporation loss caused by the heater used.



Background (1)



12



Iwatani GAS



Background (2)

Precise level control of liquid hydrogen (LH₂) is desired from the viewpoints of economy and safety.

- A liquid level gauge with high linearity and good reproducibility; superconductive MgB₂ level sensor (self-heating type) demonstrated by Haberstroh *et al.*



We propose another type (external-heating type) of MgB₂ level sensor with a short response time, operating accurately even at low liquid levels etc.



Objectives

To conduct a feasibility study of the external-heating-type MgB_2 sensor for detecting the level of LH_2 .

To elucidate the level-detecting characteristics of the MgB_2 sensor including a relatively long sensor under pressurized condition.


MgB_2 Wires Fabrication System

Liquid Hydrogen Cryostat

Liquid Hydrogen Experiment Facility




MgB₂ Level Sensor (1)



Conditions required for sc level sensor:

- 1) T_C close to LH₂ temp.
(20K@1atm-25K@3atm)
- 2) Small transition width ΔT_C
- 3) High electric resistance and small temp. dependence of resistance in normal state


MgB₂ Level Sensor (2)



LH₂ temp. (20K@1atm-25K@3atm)



MgB₂ Level Sensor (3)




MgB₂ wires with SiC impurities

In situ method
600°C × 1 h


Sample	Additive	Diameter [mm]	$T_{C,ON}$ [K]	ΔT_C [K]
D-2	None	0.65	35.4	1.6
E-4	10 % SiC	0.32	33.0	3.0
E-5	10 % SiC	0.32	31.5	3.7



In Situ Method



Resistance vs. Temperature



Liquid Hydrogen Experiment Facility



Dewar vessel →


→ LH₂ tank




Iwatani GAS




MgB₂ Sensor and Scale in LH₂ (25 K)




LH₂ Level-Detecting System




Experimental Results: V_{out} vs. $Heater_{in}$




Experimental Results: 200 mm, 0 kPaG




Experimental Results: 200 mm, 3 W



Experimental Results: 800 mm, 0 kPaG



Experimental Results: 800 mm, 9 W



Conclusion

- (1) MgB₂ wires were fabricated by the addition of 10 % SiC, and the external-heating-type level sensors (200 and 800 mm long) based on the MgB₂ wires with a resistive heater were also fabricated.
- (2) It becomes evident that the external-heating-type MgB₂ level sensor has a high linearity, a small measurement error, and a good reproducibility even under pressurized condition despite the evaporation loss caused by the heater.
- (3) Future works should be conducted to study the level-detecting characteristics under vibration conditions of a liquid surface and to make a field test for a 1-m-class prototype level sensor installed in a LH₂ tank of 2 m³.



Some Subjects for Feature Research

- (1) The development of a flowmeter for LH_2
- (2) The sloshing of the free surface of LH_2
- (3) The cavitation of LH_2
- (4) The thermal oscillation of LH_2
- (5) The rollover of LH_2
- (6) The boiling heat transfer of LH_2
- (7) The hydraulic loss of LH_2
- (8) The development of an LH_2 pump for transport

